

GERBER EDGE FX Firefile Update Version 291

2/13/2012

- If you have a GERBER EDGE FX, you must install this GERBER EDGE FX .SRE firefile update on the EDGE FX itself.
 - Do NOT load the FX firefile if you have firmware earlier than version H2.
 - The latest EDGE FX firmware is version N0. It is recommended that you load the latest EDGE FX firmware before installing this firefile. This FX firmware can be found at <http://www.gspinc.com/hardware-downloads>
 - The firmware version can be found during the start up sequence by turning the EDGE FX off and on.

NEW MATERIALS SETTINGS INCLUDED IN THIS UPDATE:

New Foils

- Electric Green
- Fireball Red

Improvements

- 280i (spot, translucent foils) 300 DPI only
- LexEDGE II Arctic White
- Composer Palettes have been added for LexEDGE 5 mil and LexEDGE Outdoor.
- Some unused materials have been removed

This firefile includes many other new materials and settings enhancements that were in previous material updates. This update overwrites any previous Materials Updates and brings the material settings to the latest version.

To Install the GERBER EDGE FX Firefile:

1. Contact GerberService before loading the firefile or firmware if you have any questions about the version, the loading or any items related to loading GERBER EDGE FX firmware.
2. Download the .SRE file from the internet and save to a known location on your hard drive.
3. Microsoft Internet Explorer® 5.5 or later is required to load the GERBER EDGE FX Firmware.
4. When the above material update.exe was run, a copy of the EDGE FX firefile (E3Fire_291_SRE.sre) was automatically extracted to your Desktop.
5. At the GERBER EDGE FX, press F1 in the MAIN MENU to set the printer OFFLINE so that it is ready for the firmware update.
6. GERBER EDGE FX *.SRE firefiles or *.GSP firmware are updated via the GERBER EDGE FX web page. Open the GERBER EDGE FX web interface by entering the printer's IP address in the Location or Address line of your web browser (Microsoft Internet Explorer 5.5 or later required) or by going to GQ Manager, right clicking on the EDGE FX, Click PROPERTIES, then click on EDGE FX Home Page link. The Welcome to GERBER EDGE FX screen displays.
7. Click the Update link to open the GERBER EDGE FX Update page. This page allows the *.SRE firefile or *.GSP firmware to be selected and sent to the GERBER EDGE FX.
8. Click the Browse button and navigate to the location of the downloaded GERBER EDGE FX firefile (E3Fire_291_SRE.sre).
9. Click the Send button to send the update file to the GERBER EDGE FX over the network. Depending on the size of the file and the network connection this may take up to a minute or more.
10. When the firmware update is complete, a status page displays the results.